

## DPA-370

### 30 WATTS BUILT-IN DIGITAL PLAYER

MEDIUM WATTAGE PA MIXER AMPLIFIER



#### FEATURES :

- 2 Mic & 1 Aux Input.
- Built-in MP3 player with USB reader and remote control.
- Bluetooth facility.
- Line Output for connecting to a Booster Amplifier.
- Cut type tone control.
- Instant transfer to DC Power (Car Battery) if AC power fails.

#### SPECIFICATIONS :

Power Output	37W Max., 30W RMS at 10% THD, 27W RMS at 5% THD
Output Regulation	= 2 dB, no load to full load at 1kHz
Input Channels	2 × Mic. 0.5mV/2.5kΩ, 1 × Aux 50mV/330kΩ
Frequency Response	100-12,000Hz ±3dB
Signal to Noise Ratio	58dB
Tone Controls	Tone: -10dB at 10kHz
Outputs	Line: 250mV/3.5kΩ
Speaker Outputs	4Ω, 8Ω, 16Ω & 100V
Digital Player	MP3 Player with USB reader
Power Supply	AC: 220-240V 50/60Hz, DC: 12-14V Car Battery
Power Consumption	AC: 48VA DC: 2.7A
Dimensions	W230 × H95 × D260 mm
Weight	4.5kg