

Hallmark of Reliability!

## DPA-570®M

### 50 WATTS WITH BUILT-IN DIGITAL PLAYER

MEDIUM WATTAGE PA MIXER AMPLIFIER

#### FEATURES :

- 3 Mic & 1 Aux Input.
- Built-in MP3 player with USB reader and remote control.
- Bluetooth facility.
- Line Output for connecting to a Booster Amplifier.
- Cut and Boost type Bass & Treble controls.
- Instant transfer to DC Power (Car Battery) if AC power fails.



#### SPECIFICATIONS :

Power Output	75W Max., 50W RMS at 10% THD, 45W RMS at 5% THD
Output Regulation	= 2 dB, no load to full load at 1kHz
Input Channels	3 x Mic 0.6mV/4.7kΩ, 1xAux 100mV/330kΩ
Frequency Response	50-15,000Hz ±3dB
Signal to Noise Ratio	55dB
Tone Controls	Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz, Line: 400mV/3.5kΩ
Speaker Outputs	4Ω, 8Ω, 16Ω & 100V
Digital Player	MP3 Player with USB, SD, MMC Card Reader & Bluetooth
Power Supply	AC: 220-240V 50/60Hz, DC: 12-14V Car Battery)
Power Consumption	AC: 90VA DC: 3.1A
Dimensions	W305 x H120 x D305 mm
Weight	6.20kg